The MB150 is a compact monoblock power amplifier that can be used as a stand-alone or modular amplifier. It can either be used as an extra amplifier for separate rooms (e.g. kitchen, bathroom, office,...), as a monitor amplifier or as an amplifier for a matrix or multiroom system.

The amplifier accepts 2 ohm loads what allows you to connect up to 8 pieces of 16 ohm loudspeakers in parallel. The front pannel of the amplifier has a volume control, headphone jack input for monitoring and a signal, protection and limit led indication. The 0/180° phase switch and 100 Hz low cut switch are some of the useful installer features on the rear pannel.

As no compromises were accepted on the component quality, the MB150 will guarantee you a perfect sound quality.

TECHNICAL SPECIFICATIONS

Input	XLR Balanced 775mV, 20 kOhm RCA Cinch, 775 mV, 10 kOhm
Output Link	Parallel to input RCA Cinch
Output Power (RMS Program)	8 Ohm: 100 watt / 140 watt Max 4 Ohm: 150 watt / 180 watt Max 2 Ohm: 170 watt / 200 watt Max
Frequency Response	20 Hz - 30 kHz
Distortion	<0.02%
Low cut	100 Hz, 12 dB/oct
Power Supply	230V
Dimensions (H x W x D)	140 x 70 x 335 mm
Weight	3.6 Kg